Midterm Exam S1 Computer Architecture

Answer on the worksheet

Duration: 1 hr. 30 min.

Last name: First name: Group:

Exercise 1 (4 points)


1. Simplify the following expressions. Give each result in a power-of-two form. Write down the result only (do not show any calculation).

Expression	Result
$\frac{32^8 \cdot 8^4 \cdot 128^7}{((1,999+49)^3 \cdot 16^{-5})^5}$	
$\frac{((8,192\cdot16^{11})^5\cdot65,536^{-8})^3}{(32^{-5}\cdot(500+12))^{-5}\cdot4,096}$	

2. How many bits do the following values contain? <u>Use a power-of-two notation</u>. Write down the result only (do not show any calculation).



 How many bytes do the following values contain? Use binary prefixes (Ki, Mi or Gi). <u>Choose the</u> <u>most appropriate prefix so that the integer numerical value will be as small as possible</u>. Write down the result only (do not show any calculation).



Exercise 2 (4 points)

Convert the following numbers from the source form into the destination form. Do not write down the result in a fraction or a power form (e.g. write down 0.25 and not $\frac{1}{4}$ or 2^{-2}). Write down the result only (do not show any calculation).

Number to Convert	Source Form	Destination Form	Result
11110001.0001	Binary	Decimal	
3FA.1	Hexadecimal	Decimal	
125.4	Decimal	Hexadecimal (2 digits after the point)	
52.0625	Decimal	Binary	
6142.153	Base 8	Hexadecimal	
7.25	Decimal	Base 5 (3 digits after the point)	
67	Base 9	Base 3	
1110101011.111011	Binary	Hexadecimal	

Exercise 3 (4 points)

Perform the following 8-bit binary operations (the two operands and the result are 8 bits wide). Then, convert the result into unsigned and signed decimal values. If an overflow occurs, write down 'ERROR' instead of the decimal value. Write down the result only (do not show any calculation).

Operation	Din aury Dagult	Decimal Value						
	Binary Result	Unsigned	Signed					
01100110 - 10011011								
10001100 + 01111110								
01111011 + 10000011								
10010011 - 10001101								

Exercise 4 (4 points) Perform the operations below. Show all calculations.

Base 2								Bas	e 16)											
			1	0	1	1		0	1	1	0)	1				F	8	C	C	
	_			1	0	1		0	0	1	1	-	0	+			3	2	В	В	
Base	e 2													Ba	Base 8						
	1	0	0	0	1	1	1	1	1	1	0	1					3	7	3	4	
														-	+		4	7	2	5	

Exercise 5 (4 points)

1. A memory has 2000_{16} addresses.

How many address lines does this memory have?

Assuming that the lowest address is 0_{16} , what is the highest address (in hexadecimal)?

2. A memory has 11 address lines.

How many addresses are available (in hexadecimal)?

Assuming that the lowest address is 0_{16} , what is the highest address (in hexadecimal)?

3. The memory space of a microprocessor is made up of 4 memory devices (M1, M2, M3 and M4). M1 and M2 both have 2000₁₆ addresses. M3 and M4 both have 11 address lines. M1 should be located in the lowest part of the memory space, followed by M2, M3 and M4. The lowest address of the memory space is 0.

Complete the table below (in hexadecimal):

M1	Lowest Address
IVI I	Highest Address
M2	Lowest Address
IVI Z	Highest Address

M2	Lowest Address
M3	Highest Address
M4	Lowest Address
1 V14	Highest Address

What is the minimum number of address lines required by the microprocessor?

Feel free to use the blank space below if you need to: