

# Key to Additional Exam S3

## Computer Architecture

Duration: 45 min

Write answers only on the answer sheet.

**Exercise 1 (3 points)**

Complete the table shown on the [answer sheet](#). Write down the new values of the registers (except the PC) and memory that are modified by the instructions. **Use the hexadecimal representation. Memory and registers are reset to their initial values for each instruction.**

Initial values:      D0 = \$0001FFFF    A0 = \$00005000    PC = \$00006000  
                           D1 = \$10000002    A1 = \$00005008  
                           D2 = \$FFFFFFFE    A2 = \$00005010

\$005000	54	AF	18	B9	E7	21	48	C0
\$005008	C9	10	11	C8	D4	36	1F	88
\$005010	13	79	01	80	42	1A	2D	49

**Exercise 2 (2 points)**

Complete the table shown on the [answer sheet](#). Give the result of the additions and the values of the N, Z, V and C flags.

**Exercise 3 (3 points)**

Let us consider the following program:

```

Main      move.l   #$00BB00BB,d7
next1     moveq.l #1,d1
           tst.b    d7
           bmi     next2
           moveq.l #2,d1
next2     clr.l    d2
           move.l   #$FFFFFFF,d0
loop2     addq.l   #1,d2
           subq.b   #1,d0
           bne     loop2
next3     clr.l    d3
           move.w   #$9999,d0
loop3     addq.l   #1,d3
           dbra    d0,loop3      ; DBRA = DBF
quit     illegal
  
```

Complete the table shown on the [answer sheet](#).

**Exercise 4 (2 points)**

Write the **IsCharError** subroutine that determines if a string that is not empty contains only digits. A string of characters ends with a null character. Except for the output registers, none of the data or address registers must be modified when the subroutine returns.

Input : **A0.L** points to a string that is not empty (i.e. that contains at least one character different from the null character).

Output : **D0.L** returns true (1) if the string contains at least one character that is not a digit.  
**D0.L** returns false (0) if the string contains only digits.

**Tips:**

- If at least one character is lower than the '0' character, you should return true (**D0.L = 1**).
- If at least one character is higher than the '9' character, you should return true (**D0.L = 1**).

**EASy68K Quick Reference v1.8**

<http://www.wowgwp.com/EASy68K.htm>

Copyright © 2004-2007 By: Chuck Kelly

Opcode	Size	Operand	CCR	Effective Address s=source, d=destination, e=either, i=displacement											Operation	Description		
	BWL	s,d	XNZVC	Dn	An	(An)	(An)+	-(An)	(iAn)	(iAn,Rn)	abs.W	abs.L	(i,PC)	(i,PC,Rn)	#n			
ABCD	B	Dy,Dx -(Ay),-(Ax)	*U*U*	e	-	-	-	-	-	-	-	-	-	-	-	-	$Dy_{10} + Dx_{10} + X \rightarrow Dx_{10}$ $-(Ay)_{10} + -(Ax)_{10} + X \rightarrow -(Ax)_{10}$	Add BCD source and eXtend bit to destination, BCD result
ADD <sup>4</sup>	BWL	s,Dn Dn,d	*****	e	s	s	s	s	s	s	s	s	s	s	s	s <sup>4</sup>	$s + Dn \rightarrow Dn$ $Dn + d \rightarrow d$	Add binary (ADDI or ADDQ is used when source is #n. Prevent ADDQ with #n.L)
ADDA <sup>4</sup>	WL	s,An	-----	s	e	s	s	s	s	s	s	s	s	s	s	s	$s + An \rightarrow An$	Add address (.W sign-extended to .L)
ADDI <sup>4</sup>	BWL	#n,d	*****	d	-	d	d	d	d	d	d	d	-	-	-	s	$\#n + d \rightarrow d$	Add immediate to destination
ADDQ <sup>4</sup>	BWL	#n,d	*****	d	d	d	d	d	d	d	d	d	-	-	-	s	$\#n + d \rightarrow d$	Add quick immediate (#n range: 1 to 8)
ADDX	BWL	Dy,Dx -(Ay),-(Ax)	*****	e	-	-	-	-	-	-	-	-	-	-	-	-	$Dy + Dx + X \rightarrow Dx$ $-(Ay) + -(Ax) + X \rightarrow -(Ax)$	Add source and eXtend bit to destination
AND <sup>4</sup>	BWL	s,Dn Dn,d	---*00	e	-	s	s	s	s	s	s	s	s	s	s	s <sup>4</sup>	$s \text{ AND } Dn \rightarrow Dn$ $Dn \text{ AND } d \rightarrow d$	Logical AND source to destination (ANDI is used when source is #n)
ANDI <sup>4</sup>	BWL	#n,d	---*00	d	-	d	d	d	d	d	d	d	-	-	-	s	$\#n \text{ AND } d \rightarrow d$	Logical AND immediate to destination
ANDI <sup>4</sup>	B	#n,CCR	=====	-	-	-	-	-	-	-	-	-	-	-	-	s	$\#n \text{ AND } CCR \rightarrow CCR$	Logical AND immediate to CCR
ANDI <sup>4</sup>	W	#n,SR	=====	-	-	-	-	-	-	-	-	-	-	-	-	s	$\#n \text{ AND } SR \rightarrow SR$	Logical AND immediate to SR (Privileged)
ASL	BWL	Dx,Dy	*****	e	-	-	-	-	-	-	-	-	-	-	-	-		Arithmetic shift Dy by Dx bits left/right
ASR	W	#n,Dy		d	-	-	-	-	-	-	-	-	-	-	-	s		Arithmetic shift Dy #n bits L/R (#n: 1 to 8)
	W	d		-	-	d	d	d	d	d	d	d	-	-	-	-		Arithmetic shift d 1 bit left/right (.W only)
Bcc	BW <sup>4</sup>	address <sup>2</sup>	-----	-	-	-	-	-	-	-	-	-	-	-	-	-	if cc true then address → PC	Branch conditionally (cc table on back) (8 or 16-bit ± offset to address)
BCHG	B L	Dn,d #n,d	---*---	e <sup>l</sup>	-	d	d	d	d	d	d	d	-	-	-	-	$\text{NOT}(\text{bit number of } d) \rightarrow Z$ $\text{NOT}(\text{bit } n \text{ of } d) \rightarrow \text{bit } n \text{ of } d$	Set Z with state of specified bit in d then invert the bit in d
BCLR	B L	Dn,d #n,d	---*---	e <sup>l</sup>	-	d	d	d	d	d	d	d	-	-	-	-	$\text{NOT}(\text{bit number of } d) \rightarrow Z$ $0 \rightarrow \text{bit number of } d$	Set Z with state of specified bit in d then clear the bit in d
BRA	BW <sup>4</sup>	address <sup>2</sup>	-----	-	-	-	-	-	-	-	-	-	-	-	-	-	address → PC	Branch always (8 or 16-bit ± offset to addr)
BSET	B L	Dn,d #n,d	---*---	e <sup>l</sup>	-	d	d	d	d	d	d	d	-	-	-	-	$\text{NOT}(\text{bit } n \text{ of } d) \rightarrow Z$ $1 \rightarrow \text{bit } n \text{ of } d$	Set Z with state of specified bit in d then set the bit in d
BSR	BW <sup>4</sup>	address <sup>2</sup>	-----	-	-	-	-	-	-	-	-	-	-	-	-	-	PC → -(SP); address → PC	Branch to subroutine (8 or 16-bit ± offset)
BTST	B L	Dn,d #n,d	---*---	e <sup>l</sup>	-	d	d	d	d	d	d	d	d	d	d	d	$\text{NOT}(\text{bit } Dn \text{ of } d) \rightarrow Z$ $\text{NOT}(\text{bit } \#n \text{ of } d) \rightarrow Z$	Set Z with state of specified bit in d Leave the bit in d unchanged
CHK	W	s,Dn	---UUU	e	-	s	s	s	s	s	s	s	s	s	s	s	if Dn=0 or Dn>s then TRAP	Compare Dn with 0 and upper bound [s]
CLR	BWL	d	-0100	d	-	d	d	d	d	d	d	d	-	-	-	-	$0 \rightarrow d$	Clear destination to zero
CMP <sup>4</sup>	BWL	s,Dn	-----	e	s <sup>4</sup>	s	s	s	s	s	s	s	s	s	s	s <sup>4</sup>	set CCR with Dn - s	Compare Dn to source
CMPA <sup>4</sup>	WL	s,An	-----	s	e	s	s	s	s	s	s	s	s	s	s	s	set CCR with An - s	Compare An to source
CMPI <sup>4</sup>	BWL	#n,d	-----	d	-	d	d	d	d	d	d	d	-	-	-	s	set CCR with d - #n	Compare destination to #n
CMPM <sup>4</sup>	BWL	(Ay)+,(Ax)+	-----	-	-	-	e	-	-	-	-	-	-	-	-	-	set CCR with (Ax) - (Ay)	Compare (Ax) to (Ay); Increment Ax and Ay
DBcc	W	Dn,address <sup>2</sup>	-----	-	-	-	-	-	-	-	-	-	-	-	-	-	if cc false then { Dn-1 → Dn if Dn < -1 then addr → PC }	Test condition, decrement and branch (16-bit ± offset to address)
DIVS	W	s,Dn	---*00	e	-	s	s	s	s	s	s	s	s	s	s	s	$\pm 32\text{bit } Dn / \pm 16\text{bit } s \rightarrow \pm Dn$	$Dn = [16\text{-bit remainder}, 16\text{-bit quotient}]$
DIVU	W	s,Dn	---*00	e	-	s	s	s	s	s	s	s	s	s	s	s	$32\text{bit } Dn / 16\text{bit } s \rightarrow Dn$	$Dn = [16\text{-bit remainder}, 16\text{-bit quotient}]$
EOR <sup>4</sup>	BWL	Dn,d	---*00	e	-	d	d	d	d	d	d	d	-	-	-	s <sup>4</sup>	$Dn \text{ XOR } d \rightarrow d$	Logical exclusive OR Dn to destination
EORI <sup>4</sup>	BWL	#n,d	---*00	d	-	d	d	d	d	d	d	d	-	-	-	s	$\#n \text{ XOR } d \rightarrow d$	Logical exclusive OR #n to destination
EORI <sup>4</sup>	B	#n,CCR	=====	-	-	-	-	-	-	-	-	-	-	-	-	s	$\#n \text{ XOR } CCR \rightarrow CCR$	Logical exclusive OR #n to CCR
EORI <sup>4</sup>	W	#n,SR	=====	-	-	-	-	-	-	-	-	-	-	-	-	s	$\#n \text{ XOR } SR \rightarrow SR$	Logical exclusive OR #n to SR (Privileged)
EXG	WL	Rx,Ry	-----	e	e	-	-	-	-	-	-	-	-	-	-	-	register ↔ register	Exchange registers (32-bit only)
EXT	WL	Dn	---*00	d	-	-	-	-	-	-	-	-	-	-	-	-	$Dn.B \rightarrow Dn.W \mid Dn.W \rightarrow Dn.L$	Sign extend (change .B to .W or .W to .L)
ILLEGAL			-----	-	-	-	-	-	-	-	-	-	-	-	-	-	PC → -(SSP); SR → -(SSP)	Generate Illegal Instruction exception
JMP		d	-----	-	-	d	-	-	d	d	d	d	d	d	d	-	$\uparrow d \rightarrow PC$	Jump to effective address of destination
JSR		d	-----	-	-	d	-	-	d	d	d	d	d	d	d	-	PC → -(SP); $\uparrow d \rightarrow PC$	push PC, jump to subroutine at address d
LEA	L	s,An	-----	-	e	s	-	-	s	s	s	s	s	s	s	-	$\uparrow s \rightarrow An$	Load effective address of s to An
LINK		An,#n	-----	-	-	-	-	-	-	-	-	-	-	-	-	-	$An \rightarrow -(SP); SP \rightarrow An;$ $SP + \#n \rightarrow SP$	Create local workspace on stack (negative n to allocate space)
LSL	BWL	Dx,Dy	***0*	e	-	-	-	-	-	-	-	-	-	-	-	-		Logical shift Dy, Dx bits left/right
LSR	W	#n,Dy		d	-	-	-	-	-	-	-	-	-	-	-	s		Logical shift Dy, #n bits L/R (#n: 1 to 8)
	W	d		-	-	d	d	d	d	d	d	d	-	-	-	-		Logical shift d 1 bit left/right (.W only)
MOVE <sup>4</sup>	BWL	s,d	---*00	e	s <sup>4</sup>	e	e	e	e	e	e	e	s	s	s	s <sup>4</sup>	$s \rightarrow d$	Move data from source to destination
MOVE	W	s,CCR	=====	s	-	s	s	s	s	s	s	s	s	s	s	s	$s \rightarrow CCR$	Move source to Condition Code Register
MOVE	W	s,SR	=====	s	-	s	s	s	s	s	s	s	s	s	s	s	$s \rightarrow SR$	Move source to Status Register (Privileged)
MOVE	W	SR,d	-----	d	-	d	d	d	d	d	d	d	-	-	-	-	$SR \rightarrow d$	Move Status Register to destination
MOVE	L	USP,An	-----	-	d	-	-	-	-	-	-	-	-	-	-	-	$USP \rightarrow An$	Move User Stack Pointer to An (Privileged)
	L	An,USP	-----	-	s	-	-	-	-	-	-	-	-	-	-	-	$An \rightarrow USP$	Move An to User Stack Pointer (Privileged)
	BWL	s,d	XNZVC	Dn	An	(An)	(An)+	-(An)	(iAn)	(iAn,Rn)	abs.W	abs.L	(i,PC)	(i,PC,Rn)	#n			

Opcode	Size	Operand	CCR	Effective Address s=source, d=destination, e=either, i=displacement											Operation	Description		
	BWL	s,d	XNZVC	Dn	An	(An)	(An)+	-(An)	(i,An)	(i,An,Rn)	abs.W	abs.L	(i,PC)	(i,PC,Rn)	#n			
MOVEA <sup>4</sup>	WL	s,An	-----	s	e	s	s	s	s	s	s	s	s	s	s	s	s → An	Move source to An (MOVE s,An use MOVEA)
MOVEM <sup>3</sup>	WL	Rn-Rn,d s,Rn-Rn	-----	-	-	d	-	d	d	d	d	d	-	-	-	-	Registers → d s → Registers	Move specified registers to/from memory (W source is sign-extended to .L for Rn)
MOVEP	WL	Dn,(i,An) (i,An),Dn	-----	s	-	-	-	-	d	-	-	-	-	-	-	-	Dn → (i,An)...(i+2,An)...(i+4,A. (i,An) → Dn...(i+2,An)...(i+4,A.	Move Dn to/from alternate memory bytes (Access only even or odd addresses)
MOVEQ <sup>4</sup>	L	#n,Dn	-***00	d	-	-	-	-	-	-	-	-	-	-	-	-	#n → Dn	Move sign extended 8-bit #n to Dn
MULS	W	s,Dn	-***00	e	-	s	s	s	s	s	s	s	s	s	s	s	±16bit s * ±16bit Dn → ±Dn	Multiply signed 16-bit; result: signed 32-bit
MULU	W	s,Dn	-***00	e	-	s	s	s	s	s	s	s	s	s	s	s	16bit s * 16bit Dn → Dn	Multiply unsig'd 16-bit; result: unsig'd 32-bit
NBCD	B	d	*U*U*	d	-	d	d	d	d	d	d	d	-	-	-	-	0 - d <sub>10</sub> - X → d	Negate BCD with eXtend, BCD result
NEG	BWL	d	*****	d	-	d	d	d	d	d	d	d	-	-	-	-	0 - d → d	Negate destination (2's complement)
NEGX	BWL	d	*****	d	-	d	d	d	d	d	d	d	-	-	-	-	0 - d - X → d	Negate destination with eXtend
NOP			-----	-	-	-	-	-	-	-	-	-	-	-	-	-	None	No operation occurs
NOT	BWL	d	-***00	-	-	d	d	d	d	d	d	d	-	-	-	-	NOT(d) → d	Logical NOT destination (1's complement)
OR <sup>4</sup>	BWL	s,Dn Dn,d	-***00	e	-	s	s	s	s	s	s	s	s	s	s	s	s OR Dn → Dn Dn OR d → d	Logical OR (ORI is used when source is #n)
ORI <sup>4</sup>	BWL	#n,d	-***00	d	-	d	d	d	d	d	d	d	-	-	-	s	#n OR d → d	Logical OR #n to destination
ORI <sup>4</sup>	B	#n,CCR	=====	-	-	-	-	-	-	-	-	-	-	-	-	s	#n OR CCR → CCR	Logical OR #n to CCR
ORI <sup>4</sup>	W	#n,SR	=====	-	-	-	-	-	-	-	-	-	-	-	-	s	#n OR SR → SR	Logical OR #n to SR (Privileged)
PEA	L	s	-----	-	-	s	-	-	-	s	s	s	s	s	s	-	↑s → -(SP)	Push effective address of s onto stack
RESET			-----	-	-	-	-	-	-	-	-	-	-	-	-	-	Assert RESET Line	Issue a hardware RESET (Privileged)
ROL	BWL	Dx,Dy #n,Dy	-***0*	e	-	-	-	-	-	-	-	-	-	-	-	-	Rotate Dy, Dx bits left/right (without X)	
ROR	W	d		d	-	-	-	-	-	-	-	-	-	-	-	-	Rotate d 1-bit left/right (.W only)	
ROXL	BWL	Dx,Dy #n,Dy	***0*	e	-	-	-	-	-	-	-	-	-	-	-	-	Rotate Dy, Dx bits L/R, X used then updated	
ROXR	W	d		d	-	-	-	-	-	-	-	-	-	-	-	-	Rotate destination 1-bit left/right (.W only)	
RTE			=====	-	-	-	-	-	-	-	-	-	-	-	-	-	(SP)+ → SR; (SP)+ → PC	Return from exception (Privileged)
RTR			=====	-	-	-	-	-	-	-	-	-	-	-	-	-	(SP)+ → CCR; (SP)+ → PC	Return from subroutine and restore CCR
RTS			-----	-	-	-	-	-	-	-	-	-	-	-	-	-	(SP)+ → PC	Return from subroutine
SBCD	B	Dy,Dx -(Ay),-(Ax)	*U*U*	e	-	-	-	-	-	-	-	-	-	-	-	-	Dx <sub>10</sub> - Dy <sub>10</sub> - X → Dx <sub>10</sub> -(Ax) <sub>10</sub> - (Ay) <sub>10</sub> - X → -(Ax) <sub>10</sub>	Subtract BCD source and eXtend bit from destination, BCD result
Scc	B	d	-----	d	-	d	d	d	d	d	d	d	-	-	-	-	If cc is true then 1's → d else 0's → d	If cc true then d.B = 11111111 else d.B = 00000000
STOP		#n	=====	-	-	-	-	-	-	-	-	-	-	-	-	s	#n → SR; STOP	Move #n to SR, stop processor (Privileged)
SUB <sup>4</sup>	BWL	s,Dn Dn,d	*****	e	s	s	s	s	s	s	s	s	s	s	s	s	Dn - s → Dn d - Dn → d	Subtract binary (SUBI or SUBQ used when source is #n. Prevent SUBQ with #n.L)
SUBA <sup>4</sup>	WL	s,An	-----	s	e	s	s	s	s	s	s	s	s	s	s	s	An - s → An	Subtract address (.W sign-extended to .L)
SUBI <sup>4</sup>	BWL	#n,d	*****	d	-	d	d	d	d	d	d	d	-	-	-	s	d - #n → d	Subtract immediate from destination
SUBQ <sup>4</sup>	BWL	#n,d	*****	d	d	d	d	d	d	d	d	d	-	-	-	s	d - #n → d	Subtract quick immediate (#n range: 1 to 8)
SUBX	BWL	Dy,Dx -(Ay),-(Ax)	*****	e	-	-	-	-	-	-	-	-	-	-	-	-	Dx - Dy - X → Dx -(Ax) - (Ay) - X → -(Ax)	Subtract source and eXtend bit from destination
SWAP	W	Dn	-***00	d	-	-	-	-	-	-	-	-	-	-	-	-	bits[31:16] ↔ bits[15:0]	Exchange the 16-bit halves of Dn
TAS	B	d	-***00	d	-	d	d	d	d	d	d	d	-	-	-	-	test d → CCR; 1 → bit7 of d	N and Z set to reflect d, bit7 of d set to 1
TRAP		#n	-----	-	-	-	-	-	-	-	-	-	-	-	-	s	PC → -(SSP); SR → -(SSP); (vector table entry) → PC	Push PC and SR, PC set by vector table #n (#n range: 0 to 15)
TRAPV			-----	-	-	-	-	-	-	-	-	-	-	-	-	-	If V then TRAP #7	If overflow, execute an Overflow TRAP
TST	BWL	d	-***00	d	-	d	d	d	d	d	d	d	-	-	-	-	test d → CCR	N and Z set to reflect destination
UNLK		An	-----	-	d	-	-	-	-	-	-	-	-	-	-	-	An → SP; (SP)+ → An	Remove local workspace from stack
	BWL	s,d	XNZVC	Dn	An	(An)	(An)+	-(An)	(i,An)	(i,An,Rn)	abs.W	abs.L	(i,PC)	(i,PC,Rn)	#n			

Condition Tests (+ OR, ! NOT, ⊕ XOR; ° Unsigned, ° Alternate cc)					
cc	Condition	Test	cc	Condition	Test
T	true	I	VC	overflow clear	IV
F	false	O	VS	overflow set	V
HI <sup>o</sup>	higher than	I(C + Z)	PL	plus	IN
LS <sup>o</sup>	lower or same	C + Z	MI	minus	N
HS <sup>o</sup> , CC <sup>o</sup>	higher or same	IC	GE	greater or equal	!(N ⊕ V)
LO <sup>o</sup> , CS <sup>o</sup>	lower than	C	LT	less than	(N ⊕ V)
NE	not equal	IZ	GT	greater than	!((N ⊕ V) + Z)
EQ	equal	Z	LE	less or equal	(N ⊕ V) + Z

**An** Address register (16/32-bit, n=0-7)  
**Dn** Data register (8/16/32-bit, n=0-7)  
**Rn** any data or address register  
**s** Source, **d** Destination  
**e** Either source or destination  
**#n** Immediate data, **i** Displacement  
**BCD** Binary Coded Decimal  
**↑** Effective address  
<sup>1</sup> Long only; all others are byte only  
<sup>2</sup> Assembler calculates offset  
<sup>3</sup> Branch sizes: **.B** or **.S** -128 to +127 bytes, **.W** or **.L** -32768 to +32767 bytes  
<sup>4</sup> Assembler automatically uses A, I, Q or M form if possible. Use #n.L to prevent Quick optimization

**SSP** Supervisor Stack Pointer (32-bit)  
**USP** User Stack Pointer (32-bit)  
**SP** Active Stack Pointer (same as A7)  
**PC** Program Counter (24-bit)  
**SR** Status Register (16-bit)  
**CCR** Condition Code Register (lower 8-bits of SR)  
**N** negative, **Z** zero, **V** overflow, **C** carry, **X** extend  
 \* set according to operation's result, = set directly  
 - not affected, **O** cleared, **I** set, **U** undefined

Revised by Peter Csaszar, Lawrence Tech University – 2004-2006

Distributed under the GNU general public use license.

Last name: ..... First name: ..... Group: .....

**ANSWER SHEET TO BE HANDED IN**

**Exercise 1**

Instruction	Memory	Register
Example	\$005000 54 AF <b>00 40</b> E7 21 48 C0	A0 = \$00005004 A1 = \$0000500C
Example	\$005008 C9 10 11 C8 D4 36 <b>FF</b> 88	No change
MOVE.W #\$5000, -(A1)	\$005000 54 AF 18 B9 E7 21 <b>50 00</b>	A1 = \$00005006
MOVE.W \$5000, -1(A1,D0.W)	\$005000 54 AF 18 B9 E7 21 <b>54 AF</b>	No change
MOVE.W \$5000(PC), -2(A1)	\$005000 54 AF 18 B9 E7 21 <b>54 AF</b>	No change

**Exercise 2**

Operation	Size (bits)	Result (hexadecimal)	N	Z	V	C
\$E2 + \$A8	8	\$8A	1	0	0	1
\$8000 + \$8000	16	\$0000	0	1	1	1

**Exercise 3**

Values of registers after the execution of the program. Use the <b>32-bit hexadecimal representation</b> .		
<b>D1</b> = \$00000001	<b>D2</b> = \$000000FF	<b>D3</b> = \$0000999A

**Exercise 4**

```
IsCharError    move.l    a0,-(a7)
\loop          move.b    (a0)+,d0
               beq      \false
               cmpi.b   #'0',d0
               blo      \true
               cmpi.b   #'9',d0
               bls      \loop
\true          moveq.l   #1,d0
               bra      \quit
\false        moveq.l   #0,d0
\quit         move.l    (a7)+,a0
               rts
```