

Midterm Exam S4

Computer Architecture

Duration: 1 hr

Write your answers only on the answer sheet.

Exercise 1 (6 points)

Complete the table shown on the [answer sheet](#). Write down the new values of the registers (except the PC) and memory that are modified by the instructions. **Use the hexadecimal representation. Memory and registers are reset to their initial values for each instruction.**

Initial values: D0 = \$FFFFFFE0 A0 = \$00005000 PC = \$00006000
 D1 = \$12340004 A1 = \$00005008
 D2 = \$FFFF0072 A2 = \$00005010

\$005000	54 AF 18 B9 E7 21 48 C0
\$005008	C9 10 11 C8 D4 36 1F 88
\$005010	13 79 01 80 42 1A 2D 49

Exercise 2 (3 points)

Complete the table shown on the [answer sheet](#). Determine the missing number for each addition in order to match the given flags (use the hexadecimal representation). **If multiple answers are possible, choose the smallest one.**

Exercise 3 (2 points)

Answer the questions on the [answer sheet](#).

Exercise 4 (3 points)

The code below has three errors. On the [answer sheet](#), specify the three line numbers that contain the errors and the three correct instructions that should have been used. The **Temp** subroutine must execute a loop whose number of iterations is specified in **D0.L**. The value of **D0.L** must be the same at the beginning and end of the subroutine.

```





1|          org      $4
2|Vector_001 dc.l    Main
3|
4|          org      $500
5|Main      move.l   #10,d0
6|          jsr      Temp
7|          illegal
8|
9|Temp      move.l   d0,-(a7)
10| \loop    subq.b  #1,d0
11|          beq     \loop
12|          move.l  +(a7),d0
13|          rts

```

Exercise 5 (6 points)

Let us consider the following program. Complete the table shown on the [answer sheet](#).

Main	<code>move.l #8640,d7</code>	
next1	<code>moveq.l #1,d1</code> <code>tst.l d7</code> <code>bmi next2</code> <code>moveq.l #2,d1</code>	
next2	<code>moveq.l #1,d2</code> <code>cmpi.b #45,d7</code> <code>blo next3</code> <code>moveq.l #2,d2</code>	
next3	<code>clr.l d3</code> <code>move.l #4004,d0</code>	
loop3	<code>addq.l #1,d3</code> <code>subq.b #1,d0</code> <code>bne loop3</code>	
next4	<code>clr.l d4</code> <code>move.w #2029,d0</code>	
loop4	<code>addq.l #1,d4</code> <code>dbra d0,loop4</code>	<code>; DBRA = DBF</code>

Opcode	Size	Operand	CCR	Effective Address s=source, d=destination, e=either, i=displacement											Operation	Description	
	BWL	s,d	XNZVC	Dn	An	(An)	(An)+	-(An)	(i.An)	(i.An,Rn)	abs.W	abs.L	(i.PC)	(i.PC,Rn)	#n		
ABCD	B	Dy,Dx -(Ay),-(Ax)	*U*U*	e	-	-	-	-	-	-	-	-	-	-	-	$Dy_{10} + Dx_{10} + X \rightarrow Dx_{10}$ $-(Ay)_{10} + -(Ax)_{10} + X \rightarrow -(Ax)_{10}$	Add BCD source and eXtend bit to destination, BCD result
ADD ⁴	BWL	s,Dn Dn,d	*****	e	s ⁴	s	s	s	s	s	s	s	s	s	s	$s + Dn \rightarrow Dn$ $Dn + d \rightarrow d$	Add binary (ADDI or ADDQ is used when source is #n. Prevent ADDQ with #n.L)
ADDA ⁴	WL	s,An	-----	s	e	s	s	s	s	s	s	s	s	s	s	$s + An \rightarrow An$	Add address (.W sign-extended to .L)
ADDI ⁴	BWL	#n,d	*****	d	-	d	d	d	d	d	d	d	-	-	-	$#n + d \rightarrow d$	Add immediate to destination
ADDQ ⁴	BWL	#n,d	*****	d	d	d	d	d	d	d	d	d	-	-	-	$#n + d \rightarrow d$	Add quick immediate (#n range: 1 to 8)
ADDX	BWL	Dy,Dx -(Ay),-(Ax)	*****	e	-	-	-	-	-	-	-	-	-	-	-	$Dy + Dx + X \rightarrow Dx$ $-(Ay) + -(Ax) + X \rightarrow -(Ax)$	Add source and eXtend bit to destination
AND ⁴	BWL	s,Dn Dn,d	-**00	e	-	s	s	s	s	s	s	s	s	s	s	$s \text{ AND } Dn \rightarrow Dn$ $Dn \text{ AND } d \rightarrow d$	Logical AND source to destination (ANDI is used when source is #n)
ANDI ⁴	BWL	#n,d	-**00	d	-	d	d	d	d	d	d	d	-	-	-	$#n \text{ AND } d \rightarrow d$	Logical AND immediate to destination
ANDI ⁴	B	#n,CCR	=====	-	-	-	-	-	-	-	-	-	-	-	-	$#n \text{ AND } CCR \rightarrow CCR$	Logical AND immediate to CCR
ANDI ⁴	W	#n,SR	=====	-	-	-	-	-	-	-	-	-	-	-	-	$#n \text{ AND } SR \rightarrow SR$	Logical AND immediate to SR (Privileged)
ASL	BWL	Dx,Dy	*****	e	-	-	-	-	-	-	-	-	-	-	-		Arithmetic shift Dy by Dx bits left/right
ASR	W	#n,Dy d	*****	d	-	-	-	-	-	-	-	-	-	-	-		Arithmetic shift Dy #n bits L/R (#n: 1 to 8) Arithmetic shift ds 1 bit left/right (.W only)
Bcc	BW ³	address ²	-----	-	-	-	-	-	-	-	-	-	-	-	-	if cc true then address \rightarrow PC	Branch conditionally (cc table on back) (8 or 16-bit \pm offset to address)
BCHG	B L	Dn,d #n,d	---*---	e ¹	-	d	d	d	d	d	d	d	-	-	-	$\text{NOT}(\text{bit number of } d) \rightarrow Z$ $\text{NOT}(\text{bit } n \text{ of } d) \rightarrow \text{bit } n \text{ of } d$	Set Z with state of specified bit in d then invert the bit in d
BCLR	B L	Dn,d #n,d	---*---	e ¹	-	d	d	d	d	d	d	d	-	-	-	$\text{NOT}(\text{bit number of } d) \rightarrow Z$ $0 \rightarrow \text{bit number of } d$	Set Z with state of specified bit in d then clear the bit in d
BRA	BW ³	address ²	-----	-	-	-	-	-	-	-	-	-	-	-	-	address \rightarrow PC	Branch always (8 or 16-bit \pm offset to addr)
BSET	B L	Dn,d #n,d	---*---	e ¹	-	d	d	d	d	d	d	d	-	-	-	$\text{NOT}(\text{bit } n \text{ of } d) \rightarrow Z$ $1 \rightarrow \text{bit } n \text{ of } d$	Set Z with state of specified bit in d then set the bit in d
BSR	BW ³	address ²	-----	-	-	-	-	-	-	-	-	-	-	-	-	PC \rightarrow -(SP); address \rightarrow PC	Branch to subroutine (8 or 16-bit \pm offset)
BTST	B L	Dn,d #n,d	---*---	e ¹	-	d	d	d	d	d	d	d	d	d	d	$\text{NOT}(\text{bit } Dn \text{ of } d) \rightarrow Z$ $\text{NOT}(\text{bit } \#n \text{ of } d) \rightarrow Z$	Set Z with state of specified bit in d Leave the bit in d unchanged
CHK	W	s,Dn	-*UUU	e	-	s	s	s	s	s	s	s	s	s	s	if $Dn < 0$ or $Dn > s$ then TRAP	Compare Dn with 0 and upper bound [s]
CLR	BWL	d	-0100	d	-	d	d	d	d	d	d	d	-	-	-	$0 \rightarrow d$	Clear destination to zero
CMP ⁴	BWL	s,Dn	-*****	e	s ⁴	s	s	s	s	s	s	s	s	s	s	set CCR with $Dn - s$	Compare Dn to source
CMPA ⁴	WL	s,An	-*****	s	e	s	s	s	s	s	s	s	s	s	s	set CCR with $An - s$	Compare An to source
CMPI ⁴	BWL	#n,d	-*****	d	-	d	d	d	d	d	d	d	-	-	-	set CCR with $d - \#n$	Compare destination to #n
CMPP ⁴	BWL	(Ay)+,(Ax)+	-*****	-	-	-	e	-	-	-	-	-	-	-	-	set CCR with $(Ax) - (Ay)$	Compare (Ax) to (Ay); Increment Ax and Ay
DBcc	W	Dn,address ²	-----	-	-	-	-	-	-	-	-	-	-	-	-	if cc false then { $Dn - 1 \rightarrow Dn$ if $Dn < -1$ then addr \rightarrow PC }	Test condition, decrement and branch (16-bit \pm offset to address)
DIVS	W	s,Dn	-***0	e	-	s	s	s	s	s	s	s	s	s	s	$\pm 32\text{bit } Dn / \pm 16\text{bit } s \rightarrow \pm Dn$	$Dn = [16\text{-bit remainder}, 16\text{-bit quotient}]$
DIVU	W	s,Dn	-***0	e	-	s	s	s	s	s	s	s	s	s	s	$32\text{bit } Dn / 16\text{bit } s \rightarrow Dn$	$Dn = [16\text{-bit remainder}, 16\text{-bit quotient}]$
EOR ⁴	BWL	Dn,d	-**00	e	-	d	d	d	d	d	d	d	-	-	-	$Dn \text{ XOR } d \rightarrow d$	Logical exclusive OR Dn to destination
EORI ⁴	BWL	#n,d	-**00	d	-	d	d	d	d	d	d	d	-	-	-	$\#n \text{ XOR } d \rightarrow d$	Logical exclusive OR #n to destination
EORI ⁴	B	#n,CCR	=====	-	-	-	-	-	-	-	-	-	-	-	-	$\#n \text{ XOR } CCR \rightarrow CCR$	Logical exclusive OR #n to CCR
EORI ⁴	W	#n,SR	=====	-	-	-	-	-	-	-	-	-	-	-	-	$\#n \text{ XOR } SR \rightarrow SR$	Logical exclusive OR #n to SR (Privileged)
EXG	L	Rx,Ry	-----	e	e	-	-	-	-	-	-	-	-	-	-	register \leftrightarrow register	Exchange registers (32-bit only)
EXT	WL	Dn	-**00	d	-	-	-	-	-	-	-	-	-	-	-	$Dn.B \rightarrow Dn.W \mid Dn.W \rightarrow Dn.L$	Sign extend (change .B to .W or .W to .L)
ILLEGAL			-----	-	-	-	-	-	-	-	-	-	-	-	-	PC \rightarrow -(SSP); SR \rightarrow -(SSP)	Generate Illegal Instruction exception
JMP		d	-----	-	-	d	-	-	d	d	d	d	d	d	d	$\uparrow d \rightarrow \text{PC}$	Jump to effective address of destination
JSR		d	-----	-	-	d	-	-	d	d	d	d	d	d	d	PC \rightarrow -(SP); $\uparrow d \rightarrow \text{PC}$	push PC, jump to subroutine at address d
LEA	L	s,An	-----	-	e	s	-	-	s	s	s	s	s	s	s	$\uparrow s \rightarrow An$	Load effective address of s to An
LINK		An,#n	-----	-	-	-	-	-	-	-	-	-	-	-	-	$An \rightarrow -(SP)$; $SP \rightarrow An$; $SP + \#n \rightarrow SP$	Create local workspace on stack (negative n to allocate space)
LSL	BWL	Dx,Dy	***0*	e	-	-	-	-	-	-	-	-	-	-	-		Logical shift Dy, Dx bits left/right
LSR	W	#n,Dy d	***0*	d	-	-	-	-	-	-	-	-	-	-	-		Logical shift Dy, #n bits L/R (#n: 1 to 8) Logical shift d 1 bit left/right (.W only)
MOVE ⁴	BWL	s,d	-**00	e	s ⁴	e	e	e	e	e	e	e	s	s	s	$s \rightarrow d$	Move data from source to destination
MOVE	W	s,CCR	=====	s	-	s	s	s	s	s	s	s	s	s	s	$s \rightarrow \text{CCR}$	Move source to Condition Code Register
MOVE	W	s,SR	=====	s	-	s	s	s	s	s	s	s	s	s	s	$s \rightarrow \text{SR}$	Move source to Status Register (Privileged)
MOVE	W	SR,d	-----	d	-	d	d	d	d	d	d	d	-	-	-	$\text{SR} \rightarrow d$	Move Status Register to destination
MOVE	L	USP,An An,USP	-----	-	d	-	-	-	-	-	-	-	-	-	-	$\text{USP} \rightarrow An$ $An \rightarrow \text{USP}$	Move User Stack Pointer to An (Privileged) Move An to User Stack Pointer (Privileged)
	BWL	s,d	XNZVC	Dn	An	(An)	(An)+	-(An)	(i.An)	(i.An,Rn)	abs.W	abs.L	(i.PC)	(i.PC,Rn)	#n		

Family Name First Name Class..... UID.....

ANSWER SHEET TO BE HANDED IN

Exercise 1

Instruction	Memory	Register
Example	\$005000 54 AF 00 40 E7 21 48 C0	A0 = \$00005004 A1 = \$0000500C
Example	\$005008 C9 10 11 C8 D4 36 FF 88	No change
MOVE.W #20500, -2(A2)		
MOVE.B 35(A0,D0.W), -1(A1)		
MOVE.L (A1)+, (A0)+		
MOVE.W (A2), -120(A1,D2.W)		

Exercise 2

Operation	Size (bits)	Missing Number (hexadecimal)	N	Z	V	C
\$7A + \$?	8		1	0	1	0
\$7A00 + \$?	16		0	1	0	1
\$7A000000 + \$?	32		1	0	0	0

Exercise 3

Question	Answer
What is the equivalent of the BGT instruction in unsigned form?	
Is the ORG directive an instruction of 68000?	

Exercise 4

Line Number	Correct Instruction

Exercise 5

Values of registers after the execution of the program. Use the 32-bit hexadecimal representation.	
D1 = \$	D3 = \$
D2 = \$	D4 = \$